

CM-331



Applications:

CM-331 converts automatically any video signal into a high resolution VGA signal. Each input has its own associated stereo audio connection, so it's easy to switch between a composite Video, S-Video or PC Input without moving around any cables.

Features:

1. Operates in NTSC 3.58, NTSC 4.43, PAL, PAL M, PAL N, SECAM automatically.
2. Superior VGA quality.
3. Adjustable control on Color, Brightness, Contrast and Tint.
4. Plug & Play - No software driver required.
5. On Screen Display (OSD) adjustment.
6. Stereo audio input and output.
7. Bypassed PC output saves the work of re-plugging when changing source between video and PC inputs

Specifications:

Input signal: 1X composite video: 1 Vp-p 75 ohm RCA jack.

1X S-V: Y/C in, 4 Pin Din connector

1X VGA: 0.7Vp-p RGB, 15 Pin D-Sub Connector.

1X S Audio(R,L)

1X V Audio(R,L)

1X PC Audio

Output signal: 1X VGA:0.7Vp-p RGB, 15 Pin D-Sub connector.

1X Audio: 47k ohm 350mVrms phone Jack.

Power supply: DC 7.5V 300mA

Dimensions: 290(W) X 145(D) X 50(H) mm

Accessory: AC Adaptor, One set of video RCA cable, one set of Audio RCA cable.

Meicheng[®] MEI CHENG AUDIO VIDEO CO., LTD

Address: 5F., NO.111, SEC. 2, HUAN HO N. RD., TAIPEI, 10376 TAIWAN

Tel: +886(2) 2585 3869,

Fax: +886(2) 2593 6672

Website: www.meicheng.com.tw

Email: mei.cheng@msa.hinet.net