

Digital Music Tutor MT-01



A. FEATURES :

Digital Music Tutor MT-01 is a special designed digital recorder for music and language learning. It is build-in 64MB flash memory to record about 60 minutes, max. 99 phases of music or vocal and save as MP3 format. You can use SD card to extend the memory capacity. You can transfer the recorded music/audio to PC or down load the music to MT-01 via USB port.

B. FUNCTION :

1. Build-in 64MB NAND FLASH MEMORY and extended SD CARD slot (Ejectable, SD CARD is not included.)
2. USB 2.0
3. Build-in omni-direction condenser microphone and two extendable microphones (L, R), 6.3 MONO jacks.
4. 3" SPEAKER X 1 , 5W AMPLIFIER OUTPUT LEVEL (RMS)
5. Extendable stereo earphone, 3.5mm stereo jack.
6. Audio line-in X 2 (RCA L&R), and line-in volume control.
7. AC POWER 110-240V OR DC 12V, 500MA
8. Volume control tune & ON/OFF button.
9. Equipped following control keys:
 - REC. (Record)
 - PLAY
 - REPEAT A-B
 - DEL. (Delete)
 - STOP
 - PAUSE
 - FAST FORWARD
 - FAST BACKWARD
 - PHASES UP/DOWN SELECTION KEYS
10. LCD PANEL DISPLAY:
 - TIMMER DISPLAY:** Hour, Minutes, Second.
 - PHASES DISPLAY:** Press phases UP/DOWN keys to select the phases.

PLAY: Press PLAY key to start up the device. The music sign will flash during the play. Press PAUSE keys that the music sign will freeze.

REC.: Press REC keys for recording. The disk sign will present while recording. STOP recording then the sign will miss.

DEL: Press **MODE**+ **▶** to delete the content. Deleting will present "dEL". When "dEL" disappeared and the clock return to 0:00:00.

A-B REPEAT: Playing music press REPEAT keys, it will present A. Press REPEAT keys again; it will present A B and repeat play between A to B till press REPEAT keys to stop the repeat.

11. Dimension: 210 (W) X 100(H) X 120(D) mm

SPECIFICATION :

1. Build-in 64MB NAND flash memory.
2. Extended memory card (SD CARD), Ejectable slot (Not include the extended SD CARD)
3. 3" SPEAKER, 5 WATT AMPLIFIER OUTPUT LEVEL (RMS)
4. USB 2.0 port
5. Sample Ratio: 128K Pps
6. Build-in microphone:
Onmi-direction condenser microphone
Balance : -64dB +/- 3dB
Frequency response: 100Hz – 12KHz
7. Earphone jacks: 3.5mm stereo
8. Line In jacks: RCA x 2, Volume control tune
9. Line Out jacks: 3.5mm stereo
10. Power:
AC 110 – 240 V & DC 12V, 500mA

Meicheng[®] MEI CHENG AUDIO VIDEO CO., LTD
Address: 5F., NO.111, SEC. 2, HUAN HO N. RD., TAIPEI, 10376 TAIWAN
Tel: +886(2) 2585 3869, Fax: +886(2) 2593 6672
Website: www.meicheng.com.tw
Email: mei.cheng@msa.hinet.net